



**ANTARES AN-193**



**ANTARES ANC-190**

### Installation


Ceiling, Surface or recessed mounting. (For recess mounting use accessories ST-21 & ST-26, see page 16)

### Optical part

Polycarbonate transparent diffuser.  
Pictograms (see page 41)

### Design

Poly carbonate housing and diffuser, manufactured in conformity with Norms EN60598-2-22 & UNE 20-392-93.  
LAMP included.



| Model           | Type | IP | Weight | Autonomy | Lumens | Battery          | Lamp         | Code       |
|-----------------|------|----|--------|----------|--------|------------------|--------------|------------|
| ANTARES AN-100  | NM   | 42 | 0,8    | 1        | 100    | 2.4 V 1.5A*h     | 8 W(G5)      | -          |
| ANTARES AN-190  | NM   | 42 | 0.9    | 1        | 153    | 3.6 V 1.5A*h     | 8 W(G5)      | 4501004010 |
| ANTARES AN-193  | NM   | 42 | 1.1    | 3        | 141    | (3.6 V 1.6A*h)x2 | 8 W(G5)      | 4501004020 |
| ANTARES AN-300  | NM   | 42 | 1.0    | 1        | 260    | 6.0 V 1.5A*h     | 8 W(G5)      | 4501006190 |
| ANTARES AN-302  | NM   | 42 | 1.1    | 2        | 250    | (6.0 V 1.6A*h)x2 | 8 W(G5)      | -          |
| ANTARES AN-400  | NM   | 42 | 1.0    | 1        | 352    | 6.0 V 1.5A*h     | PL-11 W(2G7) | 4501004030 |
| ANTARES AN-500  | NM   | 42 | 1.0    | 1        | 481    | (3.6 V 1.6A*h)x2 | PL-11 W(2G7) | 4501006480 |
| ANTARES ANM-200 | M    | 42 | 1.0    | 1        | 150    | 3.6 V 1.5A*h     | 8 W(G5)      | 4501007040 |
| ANTARES ANM-203 | M    | 42 | 1.2    | 3        | 160    | (3.6 V 1.6A*h)x2 | 8 W(G5)      | 4501007050 |
| ANTARES ANM-210 | M    | 42 | 1.1    | 1        | 170    | 3.6 V 1.5A*h     | PL-11 W(G7)  | 4501007180 |
| ANTARES ANC-190 | C    | 42 | 1.0    | 1        | 136    | 3.6 V 1.5A*h     | 8 W(G5)      | 4501004040 |
| ANTARES ANC-250 | C    | 42 | 1.1    | 1        | 246    | 6.0 V 1.5A*h     | 8 W(G5)      | 4501006500 |
| ANTARES ANC-193 | C    | 42 | 1.2    | 3        | 110    | (3.6 V 1.6A*h)x2 | 8 W(G5)      | 4501006490 |

|              |       |    |     |   |     |   |         |            |
|--------------|-------|----|-----|---|-----|---|---------|------------|
| ANTARES SIGN | AC/DC | 42 | 0.7 | - | 400 | - | 8 W(G5) | 4501007230 |
|--------------|-------|----|-----|---|-----|---|---------|------------|

|                    |    |    |     |   |     |              |             |            |
|--------------------|----|----|-----|---|-----|--------------|-------------|------------|
| ANTARES AN-100 AT  | NM | 42 | 1   | 1 | 100 | 6.0 V 1.8A*h | 8 W(G5)     | 4501007430 |
| ANTARES AN-190 AT  | NM | 42 | 1   | 1 | 153 | 6.0 V 1.8A*h | 8 W(G5)     | 4501007690 |
| ANTARES AN-300 AT  | NM | 42 | 1.0 | 1 | 260 | 6.0 V 1.5A*h | 8 W(G5)     | 4501006970 |
| ANTARES AN-400 AT  | NM | 42 | 1   | 1 | 352 | 6.0 V 1.8A*h | PL-11 W(G7) | 4501007720 |
| ANTARES AN-500 AT  | NM | 42 | 1   | 1 | 481 | 6.0 V 1.8A*h | PL-11 W(G7) | 4501007700 |
| ANTARES ANC-100 AT | C  | 42 | 1,1 | 1 | 90  | 6.0 V 1.8A*h | 8 W(G5)     | 4501007440 |
| ANTARES ANC-190 AT | C  | 42 | 1,1 | 1 | 136 | 6.0 V 1.8A*h | 8 W(G5)     | 4501007710 |
| ANTARES ANC-250 AT | C  | 42 | 1,1 | 1 | 246 | 6.0 V 1.8A*h | 8 W(G5)     | 4501007460 |
| ANTARES ANC-300 AT | C  | 42 | 1,1 | 1 | 300 | 6.0 V 1.8A*h | 8 W(G5)     | 4501007450 |

\*NM: NON MAINTAINED / M: MAINTAINED / \*C: COMBINED 2 TUBES / \*AT: AUTO TEST